

Video Recording Monitor MEMORY I PRO



Instruction Manual

Shenzhen ZO Video Technology Co., Ltd.

Packing list



Monitor*1

HDMI Cable*1

User Manual*1

Tempered Screen Protector*1

SD Card*1

Hot Shoe Mount*1

SDI Cable*1

Buttons and Ports



Catalog

1. Monitors Assist Icons	4
2. User Interface	6
3. Operation Guide	8
3.1 Boot Method	8
3.2 HDMI-SDI Interface Description	8
3.3 RGB Gain and Offset	8
3. 4 Recording And Playback	9
3. 5 Format SD Card	10
3.6 Shortcut Key Preset	10
3.7 High Precision Waveform	11
3.8 Matte	11
3.9 3D-LUT Input Method	12
3.10 3D-LUT Output Method	13
4. Notes	14
4.1 .Exceptions in Connection	14
4.2 .SD card Description	14
4.3 .Record and Playback	14
5. Technical Parameters	15

Monitors Assist Icons



Monitors Assist Icons







Lock Screen

Main Meun

User Interface



User Interface



Scope Menu

Marker Menu



Focus Menu

Exposure Menu



Color Menu

Switching Signal Menu

3.1.Boot Method

Short press the power on/off button to turn on the monitor, long press 3 seconds to turn it off.

3.2.HDMI-SDI Interface Description

SDI interface is located on the back of the host, HDMI interface is located on the side of the host, with a dedicated HDMI/SDI cable for close-up real-time monitoring.





3.3.RGB Gain and Offset Control Functions



3.4.Recording Playback

a. Custom File Name



Trigger/TimeCode camera synchronization recording function

2 This position represents the camera position, click up and down to adjust

3 This position represents the shooting site, click up and down to adjust

This position represents the number of cameras, it is not adjustable and the digital number increases with the number of shootings

3.5.Format SD Card

IN > HDM	AI 3840*2160 30	p 🕀 🖪	LUT தி	DC	7.6V
Display	Scan Noi	mal Underscan			
Recording & Playback	Backlight 50	6			
Setting	Volume	50%			
	SD card format	>			
Function	Fan status: Automatic Off	Slow Fast			
System					
Ð		+ 3	<u>ଚ</u>		=

3.6.Shortcut Key Preset

There are two shortcut keys, F1 and F2, on the top of the host, and you can choose function presets.



3.7. High Precision Waveform



3.8.Matte



3.9. 3D-LUT Input Method

IN > HDMI 3840*2160) 30p	Ð 🖪	LUT	DC	7.6V
Color menu					
LUT LUT Gamma HDR C	olorTemp				
LUT					
LUT Selection Preset	User				
LUT file XXXXXXX	xxx >				
HDMI-LUT Output					
SDI-LUT Output					
Import	Delete				
-€ 🗠 -		- 3	@ ►		-

Place the LUT file in the LUT folder on the SD card and insert the SD card into the monitor

- Click on the LUT file that needs to be loaded, then click Import and wait for the file to be imported into the system
- Click the LUT file, enter the file selection, select the desired LUT, and click to confirm that the LUT is loaded successfully

Note: LUT file name only support English, do not allow any other languages , special characters, spaces, otherwise it will fail to be imported !

3.10 3D-LUT Output Method

IN > HDMI	3840*2160 30p	Ð	í ۱	.UT	DC	7.6V
Color menu						
	HDR					
3D-LUT Gamma	HDR ColorTemp					
LUT						
LUT Selection	Preset User					
LUT file	XXXXXXXXXX >					
HDMI-LUT Output	: ()					
SDI-LUT Output						
	Import Delete					
-Ð 🔛		ϕ	3) {	\$ ►		-

Click the color management-3D-LUT icon, after opening
select the corresponding SDI-LUT output and HDMI-LUT output functions, click the

• The LUT for HDMI/SDI output is the same as the LUT that is turned on.

1.Exceptions in Connection

Zoom, Anamorphic, Waveform, these three functions can only be opened one at a time. Such as when the Anamorphic function is open, has opened the Zoom or Waveform will be forced to close

2.SD Card Description: SD Card Identification and Use Problems

2.1 The SD card of this product does not support hot-swapping, if the SD card is inserted and removed during use, causing abnormalities such as the card cannot be recognized and the screen interface cannot be operated, please restart the device.

2.2 The SD card format used in this monitor is FAT32 and it is different from the card format used in the camera, so can not be mixed.

2.3 The newly purchased SD card has to formatting by monitor's "SD Card Format" function before normal use.

2.4 Recommended card capacity is 32G-128G, MAC computers do not recognise SD cards over 32G in FAT32 format.

3. Record and Playback:

The Abnormal Phenomenon of Using Recording and Playback Synchronous recording (Trigger/TimeCode)

3.1 The camera needs to support HDMI Trigger/TimeCode

3.2 Trigger/TimeCode function is turned on

3.3 Some of the cameras have been having TimeCode output, when TimeCode mode ON, will trigger automatic recording

Technical Parameters

Model No.:	MEMORY I PRO					
Screen Size	5.5"TP					
Screen Resolution	1920*1080					
Brightness	2000cd/m ²					
Interface:	< 12W Viewing Angle: 178° (H/					
Interface:	DC In , HDMI input, SDI input, HDMI output, SDI output, 3.5mn Headphone out, SD card					
Unit Size	147.8*88.8*26.5mm					
Contrast Ratio	1200:1					
Power Supply Method	NP-F / DC IN					
Input Voltage	DC7-16V					
Weight	305g					
Video Recording Format	MP4(SD card format FAT32) ①					
LUT Format	cube file (17*17*17 and 33*33*33) ②					
Firmware Updates	SD card updates					
Audio Frequency	48kHz					
HDMI Input Signal Formats	4096*2160P25/24/23.98 3840*2160P30/23.98/25/24/23.98 1920*1080p60/59.94/50/30/29.97/25/24/23.98 1920*1080i60/59.94/50 1280*720p60/59.94/50					
SDI Input Signal Formats	1920*1080p60/59.94/50/30/29.97/25/24/23.98 1920*1080PSF30/29.97/25/24/23.98 1920*1080i60/59.94/50 1280*720p60/59.94/50					
HDMI Output Signal Formats	1920*1080p60/50/30/25/24 1920*1080i60/59.94/50 1920*p60/59.94/50					
SDI Output Signal Formats	1080p60/50/30/25/24/23.98 1080i60/50 720p60/50					
HDMI&SDI-Lut Output	support					
Please Recording file note: 2 The LUT file to be imported	It is under "Video" folder of root directory in SD card. It is under "Lut" folder of root directory in SD card, and the LUT files should not exceed 50.					





₩ FC C € @ € Tel+86 0755-21004986

URL:www.zeroone-video.com Address:2C, 2nd Floor, Building 6, Longbi Industrial Park No.27 Dafa Road, Bantian Street, Longgang District, Shenzhen Shenzhen ZO Video Technology Co., Ltd.