

MIXX 16

DIGITAL MIXER



MIXX16 Digital Mixer is a 16 inputs and 8 output digital wireless control mixer, is a new mixer through the tablet computer application control, can support all iOS, Windows 8 tablet and Android tablet. Using Wi-Fi to connect, anywhere in the wireless network within the scope of control. With 16 channels of broadcasting quality microphone amplifier (including 4 modular jack),main and aux outs. Adopt high performance 40 bit floating-point digital signal processor,24 bit AD/DA converter. Built-in effects processor, compression and limiter, gate plug-ins,parametric equalizer Wireless control mode makes you can walk between the stage and the crowd. It is 16-channel digital mixer that with the iPad and tablet computer touch.

Key Features

Practical Function

- Intuitive touch control, covering almost all the major mixing functions.
- The mixer interface can be adjusted for each channel control, including solo, mute, audio-visual, fader, you can see the full level meter.
- Tons of built-in processing. Choice of powerful, touch-sensitive plug-ins, 4-band EQ, gate and compression on inputs, 31-band GEQ and com/limiter on outputs, global reverb and delay.

Clear Sound Quality

- Ultra low-noise, high-headroom design.

Flexible Configuration

- Each channel can edit their own names and icons for easy identification, the icon can be imported from a picture library.
- Power and 48V phantom power switches and LEDs round out the mixer.
- Seamless wired to wireless mixing, turn the room from anywhere, get on stage to ring out monitors, personal monitor mixing with access control ability.

Product Specification



MIXX 16
Digital Mixer

Sample Rate:	24bit,48kHz
Frequency Respond:	20 Hz to 20 kHz +0/-1 dB
System Delay:	1.5 ms
T.H.D.:	<0.005%
Noise-Mic Input to Main Output:	-72 dBv Single channel-Max fader(A weighted) -90dBv Single channel-Min fader(A weighted)
Input Crosstalk (adjacent channel):	<-120 dB @1 kHz
S/N:	93dB Single channel-Max fader(A weighted)
Dynamic Range:	110dB Single channel-Max fader(A weighted)
CMR:	>70 dB @1 kHz
Input Impedance:	30 kΩ(1/4")
Gain:	0 to 60 dB (XLR) -20 to 40 dB(1/4")
Output Impedance:	600Ω(XLR Balance)
Max Output Level:	+21 dBu(XLR Balance)
Power Supply:	DC 12V-15V(3.5A)
Dimension(mm):	359(L)×85.5(H)×411(D)
Weight:	Approximately 4.2kg

Software Interface Instructions

- ① Channels
- ② AUX
- ③ Phantom Power
- ④ Effect
- ⑤ Channel Name
- ⑥ Compression and Gate
- ⑦ Matrix
- ⑧ Master output



INPUT EQ

- ① EQ Setting
- ② EQ Adjustable
- ③ HPF and LPF adjustable