## CLUB7-USB

00125

## DESCRIPTION

DJ mixer, 13 inputs on 7 channels (3 mics, 5 line, 2 phonos or 2 USB, 1 AUX).

## **FEATURES**

- 13 inputs on 7 channels (3 mics, 5 line, 2 phonos or 2 USB, 1 AUX)
- 2 USB connections (USB1 is Bidirectional) for connection to PC/Mac.
- Internal WMA, WAV and MP3 mediaplayer for USB memory sticks and SD card (Max 16GB / 18 folders / 2000 audio files)
- 3 separate balanced microphone inputs with talkover function
- Treble, mid, bass controls on all channels
- Assignable crossfader
- 1 Master output and 1 Booth output with individual level control.
- Master with balanced XLR outputs
- LED VU-meters on input channels and Master
- Pre-fade listening with cue mix option









**General : Application General : Dimensions (cm)**DJ & Club
48.3 x 7.8 x 22

**General: Weight (kg)** 4.32

**General : Powerinput** AC 240V, 50Hz

General: Energy Label No
General: Power consumption
W
18

**General : Color** black **General : Display** No

**General : Fixation** 19" rack mountable

General: RU No

**Connections : input** 3 pin XLR, rca, jack, usb

**Connections : output** 3 pin XLR, rca

**Function : equalizer** No **Function : sound effects** No

**Brand** JB SYSTEMS **EA NCode** 5420025601252

**Discontinued** No

YOUR DEALER

