



[Visit product page](#)



## FOS DESIGNER 1024

L005366

Lighting Controller , 1024 channels with 2 individual optical isolated DMX outputs and Net-work interface, 7" TFT-LCD touch screen for operating, 3 colour backlite keyboard, R20 library files , USB interface , flight case included , 10kg.

### TECHNICAL DETAILS

#### Technical Specifications

Channels / Universes: 1024 / 2, in optical isolated outputs with 3 pin XLR.

ArtNET output.

7" TFT - LCD touch screen.

Backlighted keys with different combinations for highlight.

Key backlighting colors: Red, Green, Yellow.

4 Optical decoders for fixture attribute control.

400 different fixtures maximum patch.

600 playbacks maximum programmable, in to 15 faders x40 pages.

15 playbacks can be simultaneously active.

400 Groups, 400 Presets, 400 users shape effects & 400 macro shows maximum.

Macro shows can be triggered by MIDI.

Color mix palette for fixtures with RGB and CMY mixing system.

Shape generator with various patterns and adjustable parameters.

More than 8000 fixtures in the library, with library editor and fixture personallity import via the USB port.

You can back up your shows in the internal hard disc, or in a USB stick.

MIDI In and Out plugs.

#### Installation / Dimension Details

Dimensions: 540 x 480 x 180 mm  
Flightcase: 575 x 575 x 235 mm  
Net Weight: 10 Kg.  
Weight including the flightcase: 19,4 Kg,

PHOTOS



PRODUCT VIDEO

