DLP-48W

B08212

DESCRIPTION

Professional digital loudspeaker management processor.

FEATURES

- 4 inputs (DIGITAL AES + analog) and 8 analog outputs with full matrix routing capability
- Direct access to 3 programmable default settings
- The 4 inputs have:
 - 8 Band equalizer (parametric, high shelf, low shelf)
 - Delay (adjustable up to 1000ms [= 346m]
 - Noisegate
 - Phase reverse
 - Gain / mute
- All 8 outputs have:
 - Flexible source selection
 - Crossover (Linkwitz/Riley, Bessel, Butterworth)
 - 6 Band equalizer (parametric, high shelf, low shelf)
 - Delay (adjustable up to 1000ms [= 346m]
 - Limiter
 - Phase reverse
 - Gain / mute
- 30 different speaker setups can be stored in the memory
- If needed, the unit can be locked via a password
- Easy parameter setup via PC:
 - Via USB: easy setup but cable length limited to 5m
 - Via LAN: long distance control for max. 250 units.
 - Via WiFi: wireless control
- Complete Windows[®] software included with visually attractive and easy setup capabilities
- Clear LCD display. Balanced XLR in/outputs







www.synq-audio.com | https://www.facebook.com/synq.audio/

Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2023 by BEGLEC NV. All rights reserved.



General : Dimensions (cm) $48 \times 4.4 \times 22$ **General : Weight (kg)** 2.62

General: Color black

General : Powerinput AC 100 - 240V, 50/60Hz

General : Energy Label No **General : Display** LCD

General : Fixation Optional 19" rack mountable

General: RU 1U
General: IP rating indoor
Audio: min. frequency (Hz) 20
Audio: max. frequency (Hz) 20000
Audio: S/N ratio (> dB) 100
Audio: max. output channels 8

Audio : functions equalizer, adjustable crossover,

limiter

Connections : input 3 pin XLR, usb, wifi, RJ45, IEC

Connections : output 3 pin XLR **Brand** SYNQ

EANCode 5420025682121



YOUR DEALER



www.synq-audio.com | https://www.facebook.com/synq.audio/