# BT-W30FC MK2

### DESCRIPTION

Extremely compact but powerful moving wash based on 3pcs CREE XML LEDs (10W RGBW) for high light output and perfect color mixing.

#### **FEATURES**

Extremely compact but powerful LED moving wash, perfect for use in clubs and discotheques but also for exhibition booths and small rental applications. Based on 3pcs CREE XML LEDs (10W RGBW) for high light output and perfect color mixing.

- Full DMX-control: 9ch (basic) or 16ch (advanced)
- Standalone or master/slave: wonderful synchronized shows with internal mic.
- SMART-DMX (previously known as DMX-MSL mode): thanks to this
  revolutionary new feature several BT-W30FC Mk2 units, working in
  master/slave, can still be controlled by 1 or 4 DMX-channels! (even
  while connected in a DMX chain, optional mini DMX splitter required)
- Optional remote controllers available: wired CA8
- Smooth but extremely fast 540° panning and 270° tilt movements
- Extremely fast strobe function
- Beam angle: 25°
- Low heat and very low power consumption
- IEC in and out connector
- Built-in menus with 4digit LED display
- Compact and stylish enclosure
- Equipped with omega brackets for fast installation









www.briteq-lighting.com | https://www.facebook.com/Briteq

Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2017 by BEGLEC NV. All rights reserved.

#### SPECIFICATIONS

**General : Application** DJ & Club, Stage & Rental

**General: Weight (kg)** 6

**General: Powerinput** AC 240V, 50Hz

General : Energy LabelNoGeneral : Power consumption W57.4General : ColorblackGeneral : Displaynone

**General : Fixation** included omega bracket

General: IP rating indoor
Control: manual No
Control: Master/Slave Yes
Control: SMART-DMX Yes

**Control : Standalone** automatic, sound

Control: optional remote CA8
Control: programmable No
Control: upgradable software No
Control: maximum DMX channels 16
Light: lamp socket none
Light: lamp

**Light : colors** Red, Green, Blue, White, Cold white

**Light: mix colors** Yes **Light: focus** None Light: zoom None Light: iris No **Light:** frost filter No **Light**: min. beam angle (°) 25 **Light**: max. beam angle (°) 25 Light: min. refresh rate (kHz) No Light: max. refresh rate (kHz) No **Brand** BRITEQ

**EA NCode** 5420025643719

**Discontinued** No

## YOUR DEALER



www.briteq-lighting.com | https://www.facebook.com/Briteq