## LED PLAND 6IN1


## DESCRIPTION

Extremely compact energy saving LED projector equipped with 7x12W RGBWA + UV LEDs!

## **FEATURES**

- Extremely compact energy saving LED projector!
- Equipped with 7x 12W RGBWA + UV LEDs
- IR-remote controller included
- Prepared for wireless DMX: just plug-in an optional WTR-DMX DONGLE
  ! (Briteq® order code: 4645)
- Different working modes:
  - **Standalone with IR-remote:** automatic or beat synchronized color patterns.
  - **Master/slave mode:** several projectors can be used together for synchronized lightshows.
  - **DMX-controlled:** different channel modes with program selection and individual color control.
  - Can be used with the **LEDCON-XL** controller!
  - Compatibility mode for the LEDCON-02 Mk2 controller (only RGB control)
- Perfect for mobile applications: extremely small and very low power consumption
- Many applications possible: Discotheques, DJs, rental companies, ...
- 0-100% dimming and ultra-fast strobe function (no additional strobes needed!)
- 4digit LED-display for easy menu navigation
- Double bracket: easy for use as floor spot!









## SPECIFICATIONS

**General: Application** DJ & Club **General**: Dimensions (cm) 21 x 13 x 23

**General**: Weight (kg)

**General: Powerinput** AC 100 - 240V, 50/60Hz

**General: Energy Label** No **General: Power consumption W** 50 **General: Color** black **General**: Display **LED General: IP rating** indoor **Control: manual** Yes **Control: Master/Slave** Yes **Control: DMX MSL** No

**Control: Standalone** automatic, sound, fixed

**Control: Type included remote** Wireless IR remote

**Control: programmable** No **Control: upgradable software** Yes **Control: maximum DMX** 9 channels **Light: lamp socket** none **Light: lamp** LED RGBWA+UV **Light: colors** 

**Light: mix colors** No Light: iris No **Light**: max. beam angle (°) 30

**Light: min. refresh rate (kHz)** No **Light**: max. refresh rate (kHz) No

**Connections: input** 3 pin XLR, IEC **Connections: output** 3 pin XLR, IEC **Brand** JB SYSTEMS **EA NCode** 5420025649612

**Discontinued** No





